# PRODUCT BRIEF - Preliminary CHL8505 HIGH EFFICIENCY 5V MOSFET GATE DRIVER

### **FEATURES**

- Ideal for Server Memory applications using +5V
- Fixed 5V Gate Drive
- Large drivers designed to drive 3nF in ≤ 15ns with +5V drive
  - Low side driver 1.5A source / 3A sink
  - High side driver 1.5A source / 3A sink
  - Transitions times & Propagation delays ≤ 15ns
- Integrated bootstrap diode
- Capable of high switching frequencies from 200kHz up to greater than 1MHz
- Compatible with CHiL's patented Active Tri-Level (ATL)
   PWM for fastest response to transient overshoot
- Non-overlap and under voltage protection
- Thermally enhanced 10 pin DFN package
- Lead free RoHS compliant package
- Low Quiescent power to optimize efficiency




Figure 1. CHL8505 pin DFN Package

#### DESCRIPTION

The CHL8505 MOSFET is a high efficiency gate driver which can switch both high-side and low-side N-channel external MOSFETs in a synchronous buck converter. It is intended for use with CHiL Digital PWM controllers to provide a total voltage regulator (VR) solution for today's advanced computing applications.

The CHL8505 driver is capable of rapidly switching large MOSFETs with low  $R_{dson}$  and large input capacitance used in high efficiency designs. It is unquiely designed to operate from a 5V source such as a system 5V or 5V standby voltages in sleep states.

The CHL8505 has a unique circuit which improves drive strength to the external MOSFETs even with just 5V supplied at the VDRV pin. This insures faster switching comparable to drivers designed for +12V drive operation. The integrated boot diode reduces external component count. The CHL8505 also features an adaptive non-overlap control for shoot-through protection.


The CHL8505 is configured to drive both the high and low side switches from the patented CHiL fast Active Tri-Level (ATL) PWM signal, which will optimize the turn off time of individual phases, optimizing transient performance.

#### **APPLICATIONS**

- Multiphase synchronous buck converter for Server CPUs and DDR Memory VR solutions
- High efficiency and compact VRM
- Optimized for Sleep state S3 systems using +5VSB
- Notebook Computer and Graphics VR solutions



## **ORDERING INFORMATION**



Package	Tape & Reel Qty	Part Number
DFN	3000	CHL8505CRT

## **PACKAGE INFORMATION & LAND PATTERN**

## DFN 3x3mm, 10 pin

